

POWER PACK 06

ENGINE	HATZ	1B40T
ALTERNATOR	MECCALTE	S16W-150
ENGINE SPEED	3000	RPM
POWER	1PH 50HZ	5.7KVA



ENGINE	HATZ
FUEL	DIESEL
GOVERNER	MECHANICALLY GOVERNED
CYLINDERS	1
ASPIRATION	NORMAL
DISPLACEMENT	0.462 LITRES
COOLING SYSTEM	AIR COOLED
EMISSION	N/A
ENGINE POWER STANDBY	7.1 KW @ 3000RPM

ALTERNATOR	MECCALTE S16W-150
POWER	5.7 KVA; 50HZ; 1PH @ 40°C
AMP	25
VOLTS	AVR CONTROLLED 230V
EXECUTION	BRUSHLESS

FUEL TANK	25L
STARTING	ELECTRIC AND RECOIL
PROTECTION	OIL, TEMP

WWW.NEWTONTTECHPOWER.CO.ZA

602 MOOIPLAATS
PRETORIA

TEL +27 (0) 824432297
FAX +27 (0) 866111090

SALES@NEWTONTTECHPOWER.CO.ZA

FUEL CONSUMPTION	
50% OF PRIME POWER	250 G/KWH
75% OF PRIME POWER	260 G/KWH
PRIME POWER	264 G/KWH